

BOM DIAL_PS15/2

Power Supply 2x15V

| No. | Quant. | Name | Value | Description |
|-----|--------|-------------|---------------------------|----------------------------------|
| 1 | 2 | C1,C2 | 220nF | 4X10R7,62 |
| 2 | 2 | C3,C4 | 2,2mF 35V | D17R7,5_ELKO Panasonic FR |
| 3 | 4 | C5,C6,C7,C8 | 100nF | C_POLYESTER_RM5,08 WIMA MKS 100V |
| 4 | 2 | C9,C10 | 470µF / 35V / 50V | D10R5,08_ELKO Nichicon UFW |
| 5 | 4 | D1,D2,D3,D4 | MUR120 | DO41 |
| 6 | 4 | D5,D6,D7,D8 | 1N4002 | DO41 |
| 7 | 1 | F1 | T0,1A / 230V T0,2A / 125V | PCB Mount Fuse |
| 8 | 1 | IC1 | MC7815 | TO220 |
| 9 | 1 | IC2 | MC7915 | TO220 |
| 10 | 2 | K1,K2 | 230V ~ | Faston 6,3mm |
| 11 | 1 | K3 | +15V | KLEMME2 anreihbar RM5 |
| 12 | 1 | K4 | -15V | KLEMME2 anreihbar RM5 |
| 13 | 2 | R1,R2 | 47 | 0207_MET |
| 14 | 1 | X2 | 70053K Talema 15VA 2x15V | TALEMA TRANSFORMER |
| 15 | 1 | | Sicherungshalter | Fuse Holder |
| 16 | 1 | | PCB | |
| 17 | 2 | | Kühlkörper | V PR5/25 M3 Heatsink |
| 18 | 1 | | Schraube M4x10 | |
| 19 | 1 | | U-Scheibe M4 | |
| 20 | 4 | | Schrauben M3x6 | |
| 21 | 2 | | U-Scheibe M3 | |
| 22 | 2 | | Federring M3 | |
| 23 | 1 | | Hülse für Flachstecker | GFSH 2X6,3 |
| 24 | 2 | | Flachstecker 6,3mm | Faston 6,3mm |