



## **DIAL-PS15/2**

### **Dual HiFi-Power Supply**

#### **Assembling and start-up:**

The board is to be assembled with the parts according to the BOM. The voltage regulators IC1 und IC2 are screwed on heatsinks, between the heatsink and the ICs must be applied thin-thermal compound. Only after the ICs have been installed the heatsinks will be attached to the PCB and then soldered to the ICs. The transformer is also screwed first and then soldered.

The 230V connection is made by two 6,3mm flat plugs, the connection cable must be pressed into the blade receptacles and the plugs inserted into the intended sleeve. Alternatively, other flat plugs with insulation can also be used.

The power supply is warmed up during operation, and a sufficient air supply is to be fitted into a housing. During assembly, a minimum distance of at least 10mm to the housing walls and other assemblies should be observed.


#### **ATTENTION:**

All works with 230V mains voltage must be carried out with special care. In the event of uncertainties, the advice of a professional is to be obtained.

The product is exclusively intended for diy.

Here, too, the current VDI/VDE guidelines apply and must be adhered to! We do not accept any liability for any resulting damage to property or personal injury. We are not liable for malfunctions, etc. which are due to non-functional applications. Anyone who builds, assembles, applies or further processes our products is exclusively at your own risk.

## Assembly and connections:



## Technical data:

- Voltage 2x15V positiv + negativ
- max. current 2x200mA
- Mains voltage 230V
- Power 15VA
- Noise 0,002% / 10µV/V
- Weight 365g
- Measures (LxWxH) 122 x 70 x 32mm

Copyright 2017 by DIAL-audio

DIAL audio  
Alexander Dittmar  
Windmühlenstraße 22  
08523 Plauen

[www.dial-audio.de](http://www.dial-audio.de)  
[info@dial-audio.de](mailto:info@dial-audio.de)